MHK5 ÉRZÉKELŐ

MHK515-PROF-001


- Felbontás max. 25 bites; 13 bit a felbontáshoz és 12 bites a fordulathoz
- CANopen, DeviceNet, Ethercat, Ethernet / IP, Interbus, Modbus, Párhuzamos, Profibus, Profinet
- IP64



TERMÉKLEÍRÁS


MŰSZAKI ADATOK


Befoglalási átmérő	58 mm
Csatlakozás	Csavaros csatlakozás
Érzékelő típusa	Abszolút
IP-osztály	IP64
Kilépés	Profibus
Max. sebesség	6000 rpm
Max. tápfeszültség, DC	30 V DC
Max. üzemi hőmérséklet	85 °C
Min. tápfeszültség, DC	10 V DC
Min. üzemi hőmérséklet	-40 °C
Tengelyátmérő	15 mm
Verzió	Többmenetes



PROGRAMMABLE PARAMETERS

Operating Parameters	This parameter determines the counting direction, in which the output code increases or decreases. As an important operating parameter the code sequence (complement) can be programmed
Resolution per turn	Value between 1 and 8192 can be programmed
Total resolution "Max range"	This parameter is used to program the desired number of measuring units over the total measuring range. This value may not exceed the total resolution of the absolute rotary encoder.
Preset Value	The preset value is the desired position value, which should be reached at a certain physical position of the axis
Limit Switch, Min. and Max	Two position values can be programmed as limit switches. By reaching these values one bit of the 32 bit process value is set to high level
Cam	One free programmable cam can be set in the total measuring range





PROGRAMMABLE PARAMETERS

Operating Parameters	This parameter determines the counting direction, in which the output code increases or decreases. As an important operating parameter the code sequence (complement) can be programmed
Resolution per turn	Value between 1 and 8192 can be programmed
Total resolution "Max range"	This parameter is used to program the desired number of measuring units over the total measuring range. This value may not exceed the total resolution of the absolute rotary encoder.
Preset Value	The preset value is the desired position value, which should be reached at a certain physical position of the axis
Limit Switch, Min. and Max	Two position values can be programmed as limit switches. By reaching these values one bit of the 32 bit process value is set to high level
Cam	One free programmable cam can be set in the total measuring range